





WRF Tutorial July 2019

Idealized Cases: 2d flow over a bell-shaped mountain

Sounding File Format

File: WRF/test/em quarter ss/input sounding

		surface	_ 1	_	0
	surface	potential	surface vapor		
	Pressure	Temperature	mixing ratio		
	(mb)	(K)	(g/kg)		
line 1	1000.00	300.00	14.00		
	250.00	300.45	14.00	-7.88	-3.58
. /	750.00	301.25	14.00	-6.94	-0.89
each /	1250.00	302.47	13.50	-5.17	1.33
successive	1750.00	303.93	11.10	-2.76	2.84
line is a	2250.00	305.31	9.06	0.01	3.47
point in the	2750.00	306.81	7.36	2.87	3.49
sounding	3250.00	308.46	5.95	5.73	3.49
	3750.00	310.03	4.78	8.58	3.49
	4250.00	311.74	3.82	11.44	3.49
	4750.00	313.48	3.01	14.30	3.49
	height (m)	potential temperature (K)	vapor mixing ratio (g/kg)	U (west-east) velocity (m/s)	V (south-north) velocity (m/s)
VRF Tutorial July 2019				Bill Skamarock (skamaroc@ucar.edu)	

Idealized Cases: 2d squall line

squall2d x is (x,z), squall2d y is (y,z); both produce the same solution.

Initialization code is in

WRF/dyn em/module initialize ideal.F This code also introduces the initial perturbation.

The thermodynamic soundings and hodographs are in the ascii input files WRF/test/em squall2d x/input sounding WRF/test/em squall2d y/input sounding

WRF Tutorial July 2019

Bill Skamarock (skamaroc@ucar.edu)





Idealized Cases: baroclinic wave in a channel

Height coordinate model (dx = 100 km, dz = 250 m, dt = 600 s) Surface temperature, surface winds, cloud and rain water



WRF Tutorial July 2019

Bill Skamarock (skamaroc@ucar.edu)

Idealized Cases: baroclinic wave in a channel

Default configuration in <u>WRF/test/em_b_wave/namelist.input</u> runs the dry jet in a periodic channel with dimension

(4000 x 8000 x 16 km) (x,y,z).

Turning on any microphysics (mp_physics > 0 in namelist.input) puts moisture into the model state.

The initial jet only works for dy = 100 km and 81 grid points in the y (south-north) direction.

Idealized Cases: baroclinic wave in a channel

Initialization code is in WRF/dyn_em/module_initialize_ideal.F

The initial jet (y,z) is read from the binary input file <u>WRF/test/em_b_wave/input_jet</u>

The initial perturbation is hardwired in the initialization code.

WRF Tutorial July 2019

Bill Skamarock (skamaroc@ucar.edu)



